

High Temperature Guard

Temperature Monitor and Alarm

Models VM520, VM520-DCP-E

Manual and Installation Instructions

For units purchased since June 2006

Index	Page
Wiring Diagram	4
Installation	5
Accessing the Refrigerator/Freezer Guard over the phone	6
Programming Temperature Sensor Parameters	6-8
Programming Door Sensor Inputs	9
Programming the Autodialer Functions	10-13
Programming Contact Telephone Numbers	10
Programming Local ID Number	11
Recording a Unit ID Message	11
Programming the Number of Rings	11
Programming PIN Numbers	12
Programming Reminder Calls	12
Programming Warning Message Repetitions	13
Set Temperature Readout (°C or °F)	13
Programming Power Outage Delay Time	13
Changing the Callout Delay Time	14
Using the Refrigerator/Freezer Guard	14
Checking Sensor Inputs Locally	14
Checking Sensor Inputs Remotely	14
Clearing High and Low Temperature Readings Locally	15
Clearing High and Low Temperature Readings Remotely	15
Confirming Alarm Conditions Remotely	15
Confirming Alarm Conditions Locally	15
Interpreting the Display	16-18
Frequently Asked Questions	19-20
Troubleshooting	20
Advanced Network Setup	21
FCC Part 68 Information	22
Limited Warranty	23

General Description

The High Temperature Guard is a complete temperature monitor and alarm system with integrated autodialer.

The High Temperature Guard monitors up to four (4) K-type thermocouple temperature sensors, one (1) dry contact alarm input, and power.

The High Temperature Guard has programmable high and low temperature limits and an alarm time delay for each sensor. An identification message can be recorded for each sensor, indicating where the sensor is located to allow a quick response to a problem. The High Temperature Guard has numerous options that allow it to be configured for any application.


The High Temperature Guard can monitor any switch, relay, or dry contact with its dedicated dry contact input. A time delay can be programmed, enabling a contact to be closed a maximum amount of time before the buzzer is activated and the High Temperature Guard begins its alarm procedures.

The High Temperature Guard will turn on the alarm relay and buzzer and begin making emergency notification calls when the temperature of any sensor is out of limits for greater than the alarm time delay or if the dry contact input is active.

The Ethernet Data Collection Package version (VM520-DCP-E) allows you to collect data across your LAN and store readings on PC. Also, alert emails can be sent out to alert staff to temperature issues. A built-in web server allows you to use a simple web browser to check the temperatures by entering the IP address of the device into a web browser.

Wiring Diagram

Plug in Thermocouple Terminals



K type thermocouples with integrated spade connectors

Installing the High Temperature Guard

- Select a location with access to power and an analog telephone line.
- Mount the High Temperature Guard to the wall.
- Connect the phone line to an active **analog** telephone jack.
It is recommended that a surge suppresser be used for the phone line.
- Plug the power pack into a 120vac power outlet.
- **It is recommended that a surge suppresser be used for the power line.**
- Plug the Ethernet cable into the **LAN** jack (for VM520-DCP-E units)
- **Connect Sensors and Inputs**
Temperature Sensors must be installed before turning on the unit.
- Turn on the High Temperature Guard by moving the power switch to the left of the terminal blocks to the “1” position.

For VM520-DCP-E units:

- Download the Data Capture software from:
<http://www.temperatureguard.com/datacapture>
- **Set the IP address of your Temperature Guard**
Run the Temperature Guard IP Address Setup program.
Click on the red button to find all of the Temperature Guard devices on your network. A list of their IP address' are displayed.
Click on the IP address of the Temperature Guard device which you are setting with a new IP address. The selected IP address will turn yellow.
Type in a free and **valid** static IP address (contact your IT Administrator for assistance.)
Click on the green button to set the selected Temperature Guard's current IP address to the new static IP address. You will be prompted to confirm this change. Click OK to proceed. This process will take approximately 2 minutes. The program will once again find all of the Temperature Guards on your network. Please verify that the IP address has been changed. If not repeat the above procedure.
See the Troubleshooting section for assistance with network issues.
- **Collect data from your Temperature Guard**
Please see the Data Capture Manual for detailed instructions on using the Data Capture Program.

Accessing the High Temperature Guard over the phone

- 1 From another phone line call the High Temperature Guard. The device will pick up after the programmed number of rings (Default is 1).
- 2 To access all functions, enter the 4-digit "Full Access" PIN. (Factory default is 0000). To access only the "Acknowledge Only" functions, enter the 4-digit "Acknowledge Only" PIN 1234.
The "Acknowledge Only" functions are:
 - A) Confirming Alarm Conditions Remotely
 - B) Checking Sensor Inputs Remotely
- 3 You will hear the Main Menu options:

Main Menu	
Option	Function
1	Status
2	Set Limits
3	Program
#	<i>Repeat Warning message (if any input is in alarm condition)</i>
0	Exit (Hang Up the phone)

NOT SPOKEN MENU ITEM

Programming Temperature Sensor Parameters

Each temperature sensor has four (4) programmable parameters as well as a programmable temperature correction.

Sensor Identification Message. The Sensor ID message will be played when the High Temperature Guard is reporting the status of that Sensor.

Sensor Low and High Temperature limits. The low and high temperature limit values are programmed in degrees. When a sensor's temperature exceeds either the high or low limit for longer than the programmed callout time delay, that sensor will be in alarm condition. For VM520-DCP-E units this value can also be programmed using the Data Capture Software.

Sensor callout time delay. A sensor's temperature must be out of limits for greater than the callout delay time for the sensor to be in alarm condition. For VM520-DCP-E units this value can also be programmed using the Data Capture Software.

Programming Sensor Parameters

1. Accessing the Sensor Configuration

- a) From the Main Menu, press 2 to Set Limits
 - ▶ The "Full Access" PIN will be requested if the "Acknowledge Only" PIN was entered initially. If the correct "Full Access" PIN is not entered, the High Temperature Guard will hang up.
- b) You will hear "Enter Sensor Number"
- c) Enter the sensor you want to program (1-4)
 - ▶ To return to the Main Menu press 0
- d) Proceed to Step 2.a.

2. Programming the Sensor ID message

- a) You will hear "Sensor x message is"
- b) You will hear "Press 1 to change"
- c) Press 1 to change the message
 - ▶ Press 2 to skip and proceed to step 3.a or press 0 to stop programming this sensor and return to step 1.b



TIP

Record something specific that will allow the people receiving the alarm calls to understand where the problem is.

- d) You will hear a tone
- e) Begin speaking after the tone. The High Temperature Guard will record for about 3 1/2 seconds
- f) After 3 1/2 seconds you will hear the tone again, marking the end of your message
- g) You will hear the message you recorded
- h) Proceed to step 3.a

3. Programming the Lower and Upper Temperature Limits

- a) You will hear "Sensor x lower limit is" and the current low temperature limit for that sensor (i.e. 35°)
- b) You will hear "Press 1 to change"
- c) Press 1 to change the limit
 - ▶ Press 2 to skip and proceed to step 3.g or press 0 to stop programming this sensor and return to step 1.b
- d) You will hear "Enter number then press pound"
- e) Enter the value then press #.
 - ▶ Use * to program a negative number (i.e. *20 = -20°)
 - ▶ Acceptable range is -999 to 999
- f) You will hear the value you just entered (i.e. 39°)
- g) You will hear "Sensor x upper limit is" and the current high temperature limit for the selected sensor (i.e. 60°)
- h) You will hear "Press 1 to change"
- i) Press 1 to change the limit
 - ▶ Press 2 to skip and proceed to step 3.g or press 0 to stop program-

- ming this sensor and return to step 1.b
- j) You will hear "Enter number then press pound"
- k) Enter the value then press #.
 - ▶ Use * to program a negative number (i.e. *20 = -20°)
 - ▶ Acceptable range is -999 to 999
- l) You will hear the value you just entered (i.e. 50°)
- m) Proceed to step 4.a

4. Programming the callout delay time

- a) You will hear "Callout time delay is x minutes press 1 to change" (default 0 minutes)
- b) Press 1 to make a change
 - ▶ Press 2 to skip and return to step 1.b
- c) You will hear "Enter number then press pound"
- d) Enter the time delay in minutes (i.e. 15 for 15 minutes or 0 minutes for an immediate callout)
 - ▶ Acceptable range is 0 to 900 minutes
- e) You will hear the value you just entered
- f) Proceed to step 1.b

Repeat the steps 1 to 4 for each additional sensor.

Programming Temperature Corrections

The High Temperature Guard allows the user to correct for small temperature measurement errors due to sensor cable extension length for each sensor. A calibrated standard must be used to obtain the actual temperature.

- a) From the Main Menu, press 2 to Set Limits
- b) You will hear "Enter Sensor Number"
- c) Enter the pound sign ("*# button*")
- d) You will hear "Enter Sensor Number *to Adjust*"
- e) Enter the number of the sensor you want to correct (1-4)
 - ▶ To return to the Set Limits Menu press 0
- f) You will hear "Enter Sensor Number *x Actual Temperature, then press pound*"
- g) Enter the actual temperature measured using the standard, then press #.
 - ▶ The maximum the temperature measurement can be corrected is +-25° from the currently displayed temperature.
(i.e. If the temperature currently being displayed is 100°, the max correction is 125° and the min correction is 75°. An "invalid" message is played for larger corrections.)
- h) You will hear the corrected temperature and the corrected temperature will be displayed on the display.

Programming the Alarm Input

The Alarm Input is a dry contact alarm input which will go into alarm condition and generate alert callouts if a switch or contact is closed across the input for longer than the programmed alarm time delay. Note that when system power is off, the relay and alarm will not operate.

- a) From the Main Menu, press 2 to set Limits
- b) You will hear "Enter Sensor Number"
- c) Enter 5
 - ▶ To return to the Main Menu press 0
- d) You will hear "Alarm Input callout time delay is xx minutes press 1 to change" (default 0 minutes)
- e) Press 1 to make a change or press any other button to not make a change
- f) You will hear "Enter number then press pound"
- g) Enter the time delay in minutes (i.e. 15 for 15 minutes or 0 minutes for an immediate callout)
 - ▶ Acceptable range is 0 to 900 minutes
 - You will hear the value you just entered
- h) You will be returned to the Set Limits Menu

Programming the Autodialer Functions

Accessing the Program Menu

From the Main Menu, press 3

- ▶ The "Full Access" PIN will be requested if the "Acknowledge Only" PIN was entered initially. If the correct "Full Access" PIN is not entered, the High Temperature Guard will hang up.

Program Menu	
Option	Function
1	Program Contact Telephone Numbers
2	Program Local ID Number
3	Record Unit ID Message
4	Program Number of Rings
5	Change "Full Access" PIN
6	Program Reminder Calls
7	Program Repeat Warning Messages
8	Set Temperature Readout Units (°C or °F)
9	Program Power Outage Delay Time
*	Change Callout Time Delay
#	Change "Acknowledge Only" PIN
0	Exit (return to Main Menu)

NOT SPOKEN

Programming Contact Telephone/Pager Numbers

The High Temperature Guard stores up to four (4) contact telephone or pager numbers.

- 1 From the Program Menu, Select **1** to set telephone numbers.
- 2 You will hear "*Select contact one to four*"
- 3 Select **1** for the first contact number, **2** for the second contact number, **3** for the third contact number, or **4** for the fourth contact number.
 - ▶ Press 0 to return to the Program Menu.
- 4 You will hear "*Contact x is xxxxxx*" or "*Contact x is Empty, press one to change*"
- 5 Press **1** to make a change or enter a telephone number.
- 6 You will hear "*Enter number then press pound*"
- 7 Enter the number, followed by a **#**
 - ▶ For pager numbers, enter * as the first digit of the number
 - ▶ Enter the full telephone number (**1 + area code if necessary**)
 - ▶ If an extra delay between digits or after dialing is required, entering *

will provide a two second delay. Do not enter * for the first digit unless programming a pager number.

▶ Entering only the # key will erase the currently programmed contact telephone number.

- 8 You will hear the telephone number you just entered.
- 9 You will be prompted to select another contact to program.
 - ▶ Press 0 to return to the Program Menu.

Programming a Local Identification Number For Pagers

The local ID number is printed on a pager's display, when calls are made to a pager. The ID number can be up to 20 digits long.

- 1 From the Program Menu, press **2** for the local ID
- 2 You will hear the programmed number or the High Temperature Guard will say "Empty"
- 3 You will hear *"Press one to change"*
- 4 Press **1** to make a change or **2** to return to the Program Menu
- 5 You will hear *"Enter number, then press pound"*
- 6 Enter the number, followed by a **#**
- 7 You will hear the number you just entered.
- 8 You will be automatically returned to the Program Menu

Recording a Unit Identification Message

During callouts, this message is played to identify the unit. Record a message to help ID where the High Temperature Guard is located.

- 1 From the Program Menu, press **3** to record a message
- 2 If this is the first time setup, go to step 4
- 3 You will hear the recorded message
- 4 You will hear *"Press one to change."*



TIP

Record something to identify where the monitor is located to allow people receiving the alarm calls to understand what is calling them. "Springfield Pediatrics vaccine temp monitor" or "ABC Cold Storage warehouse 3" are two good examples of useful messages.

- 5 Press **1** to make a change or **2** to return to the Program Menu
- 6 You will hear a tone
- 7 Begin speaking after the tone. The High Temperature Guard will record for about 4 seconds
- 8 After 4 seconds you will hear the tone again, marking the end of your message
- 9 You will hear the message you recorded
- 10 You will be automatically returned to the Program Menu

Programming the Number of Rings

The High Temperature Guard answers the telephone line after the programmed number of rings. Valid rings are 1 – 25. The setting can be used to enable the High Temperature Guard to share a line with another device.

See the Frequently Asked Questions section for details.

- 1 From the Program Menu, press **4** to set the number of rings
- 2 You will hear the programmed number of rings
- 3 You will hear *"Press one to change."*
- 4 Press **1** to make a change or **2** to return to the Program Menu
- 5 You will hear *"Enter number then press pound"*
- 6 Enter the number of rings, then press **#**
- 7 You will hear the number of rings you entered
- 8 You will be automatically returned to the Program Menu

Programming the "Full Access" PIN Number

The High Temperature Guard has a programmable "Full Access" 4-digit PIN number (0000-9999) to allow users to access the Set Limits option and Program sub-menu, and to confirm alarm conditions.

PIN number must be 4 digits and must not include a # sign.

- 1 From the Program Menu, press **5** to change the "Full Access" PIN
- 2 You will hear the programmed PIN number
- 3 You will hear *"Press one to change."*
- 4 Press **1** to make a change or **2** to return to the Program Menu
- 5 You will hear *"Enter number"*
- 6 Enter a four digit number
- 7 You will hear the PIN number you just entered
- 8 You will be automatically returned to the Program Menu

Programming the "Acknowledge Only" PIN Number

The High Temperature Guard has a programmable "Acknowledge Only" 4-digit PIN number (0000-9999) to allow users to only to confirm alarm conditions.

PIN number must be 4 digits and must not include a # sign.

- 1 From the Program Menu, press **#** to change the "Acknowledge Only" PIN
 - 2 You will hear the programmed PIN number
 - 3 You will hear *"Press one to change."*
 - 4 Press **1** to make a change or **2** to return to the Program Menu
 - 5 You will hear *"Enter number"*
 - 6 Enter a four digit number
 - 7 You will hear the PIN number you just entered
- You will be automatically returned to the Program Menu

Programming Reminder Calls

If a temperature is out of limits or a High Temperature door remains open after the alarm has been acknowledged, the High Temperature Guard can make "reminder calls". This feature alerts personnel that a problem still exists, and has not been fixed. The reminder call delay can be programmed from 15 to 900 minutes.

- 1 From the Program Menu, press **6**
- 2 You will hear "Off"
- 3 You will hear *"Press one to change."*

- 4 Press **1** to change this setting, or 2 to return to the Program Menu.
- 5 You will hear "On"
- 6 You will hear "Callout time delay is XX minutes press 1 to change"
(Default value is 60 minutes)
- 7 Press 1 to make a change or press 2 to not make a change
- 8 You will hear "Enter number then press pound"
- 9 Enter the time delay in minutes (i.e. 120 for 2 hours)
- 10 You will hear the value you just entered
- 11 You will be automatically returned to the Program Menu

Programming Warning Message Repetitions

During callouts the High Temperature Guard will repeat the local ID message and warning conditions a programmable number of times (Default 1 repetition)

- 1 From the Program Menu, press **7**
- 2 You will hear "Warning Reminder is 1"
- 3 You will hear "*Press one to change.*"
- 4 Press **1** to change this setting, or 2 to return to the Program Menu.
- 5 You will hear "Enter number then press pound"
- 6 Enter the number of times (0,1, or 2) that you would like the warning message repeated.
- 7 You will hear the value you just entered
- 8 You will be automatically returned to the Program Menu

Set Temperature Readout Units (°C or °F)

The High Temperature Guard can display and report temperature readings in degrees Celsius or Fahrenheit.

- 1 From the Program Menu, press **8**
- 2 You will hear "*Degrees is 32, press one to change*", indicating the temperature reading at freezing in its current mode. (Default is Fahrenheit)
- 3 Press **1** to switch to Celsius Temperature Readout, or 2 to return to the Program Menu.
- 4 You will hear "*Degrees is 0*"
- 5 You will be automatically returned to the Program Menu

Program Power Outage Delay Time

The High Temperature Guard can delay a programmable amount of time before alarming due to a power outage. The default time is 5 minutes.

- 1 From the Program Menu, press **9**
- 2 You will hear "*Power callout time delay is 5 minutes press 1 to change*"
- 3 Press 1 to change, or 2 to return to the Program Menu
- 4 You will hear "*Enter number then press pound*"
- 5 Enter the time delay in minutes (i.e. 15 for 15 minutes or 0 minutes for an immediate callout)
 - ▶ Acceptable range is 0 to 120 minutes
- 6 You will hear the value you just entered
- 7 You will be automatically returned to the Program Menu

Changing the Callout Delay Time

When a refrigerator or freezer's temperature is out of range the High Temperature Guard will wait this programmable amount of time before making telephone alert calls. (Default 2 minutes)

- 1 From the Program Menu, press *
- 2 You will hear "Callout Time Delay is 2 minutes"
- 3 You will hear "*Press one to change.*"
- 4 Press **1** to change this setting, or **2** to return to the Program Menu.
- 5 You will hear "Enter number then press pound"
- 6 Enter the time delay in minutes (i.e. 60 for 1 hour)
- 7 You will hear the value you just entered
- 8 You will be automatically returned to the Program Menu

Using the High Temperature Guard

Application notes can be downloaded from the documentation section of our website at www.TemperatureGuard.com.

Checking Sensor Inputs Locally

All temperature sensors connected will have their temperature readings displayed next to the sensor number on the display. High and low readings are displayed on the right side of the display in the status window at 2 second intervals.

Checking Status Remotely with a telephone call

- 1 Call the High Temperature Guard
- 2 Enter your PIN number
- 3 From the main menu press **1**
- 4 You will hear "Enter Sensor Number"
- 5 Enter the number of the sensor you wish to hear (i.e. 1) or enter 9 to hear the status of the Dry Contact Input
- 6 For Temperature Sensor Inputs, you will hear the sensor's temperature and the highest and lowest reading, and how long the sensor has been out of limits in minutes.
For the Dry Contact Inputs, you will hear the status of the input, unless power is out.
- 7 You will hear the current power status

Checking Status Remotely with a web browser (VM520-DCP-E)

- 1 Open a web browser such as Internet Explorer.
- 2 Enter the IP address of the device for the URL address.
- 3 The status of all connected sensors will be displayed.

Clearing High and Low Temperature Readings Locally

High and low temperature readings can be cleared by holding the black

pushbutton on the front of the enclosure down for at least 5 seconds while that sensor's data is being displayed.

Clearing High and Low Temperature Readings Remotely

- 1 Call the High Temperature Guard
- 2 Enter the "Full Access" PIN number
- 3 From the main menu press **1**
- 4 You will hear "Enter Sensor Number"
- 5 Press **#**
- 6 You will hear "Enter Sensor Number to Change"
- 7 Enter the number of the sensor whose min and max readings you wish to reset to the current temperature.

Confirming Alarm Conditions Remotely

During callouts, the High Temperature Guard will prompt you to enter a PIN number, enter either the Full Access PIN or "1234", the Acknowledge Only PIN.

If you have received a page or a voice mail message regarding an alarm condition that you wish to confirm. Simply call the High Temperature Guard and enter either the Full Access PIN or "1234", the Acknowledge Only PIN, The alarm relay will de-energize, and the High Temperature Guard will stop making callouts for the current alarm condition. **This action does not override the Reminder Call feature.**

Confirming Alarm Conditions Locally

To confirm an alarm condition locally push the black button on the left side of the High Temperature Guard. The alarm relay will de-energize, and the High Temperature Guard will stop making callouts for the current alarm condition. **This action does not override the Reminder Call feature.**


Interpreting the Display

Start Up

When starting up, the High Temperature Guard checks each temperature sensor input to verify that a sensor is connected.


If a sensor is connected and has a reading within range, "ok" will be printed next to that sensors label.

If a sensor is not connected or has a reading out of range, "n/c" will be printed next to that sensors label.



Sensor Reading

The High Temperature Guard continuously displays all temperature measurements, and the highest and lowest recorded temperatures of each sensor on the right hand side of the screen.



Alarm Conditions

When an alarm condition occurs, the alarm relay and buzzer are activated and the High Temperature Guard waits 2 minutes before making callouts.

The time remaining before alarm callouts commence is displayed.


During this time, onsite personnel can cancel the emergency by pressing the black alarm acknowledge button on the face of the High Temperature Guard.

1: 51 >	CALL-
2: 28	OUTS
3:	IN
4:	01:58

Alarm Callouts

When the High Temperature Guard is making callouts, the status is displayed in the right side of the screen.

While the High Temperature Guard is making telephone calls, the display is not updated with new temperature readings.



Sensor Reading After Callouts

If the High Temperature Guard has called all programmed telephone numbers and not made contact it will wait 20 minutes before attempting to callout again. Periodically, the time before callouts resume will be displayed.

1: 510 >	CALL-
2: 200	OUTS
3:	IN
4:	17:25

Frequently Asked Questions

When does the High Temperature Guard callout?

The High Temperature Guard will callout when any sensor/input is in an alarm condition and has not been confirmed.

When an alarm condition first occurs, the High Temperature Guard turns on the alarm relay and buzzer, and then waits two minutes to allow local personnel time to react to the alarm.

When is a sensor/input in alarm condition?

When a temperature sensor has been out of limits for greater than the programmed time delay.

When a temperature sensor opens or shorts after having been connected.
When a door sensor has been open longer than the programmed time delay.

When the power has been out for greater than five minutes.

What happens when the High Temperature Guard calls?

- 1 The High Temperature Guard will dial the contact number exactly as it was programmed.
 - ▶ If the contact number was programmed as a pager number (* is the first digit. The High Temperature Guard will dial all digits following the *.
- 2 The High Temperature Guard will wait for a person or voice mail system to answer the call.
- 3 The High Temperature Guard will beep while it waits for a person to stop speaking or the voice mail system's outgoing message to stop.
- 4 For voice contact numbers, the High Temperature Guard will play the recorded personal identification message.
For pager contact numbers, the High Temperature Guard will print the Local Identification number on the pager screen. The High Temperature Guard will then hang up and call the next programmed contact number.
- 5 The High Temperature Guard will report any alarm conditions (i.e. "Warning, Sensor 2, *sensor 2 recorded message*", *is 89 degrees and has been out of limits for, x hours and y minutes*).
- 6 The High Temperature Guard will ask for the PIN number.

Once the PIN number has been entered, the High Temperature Guard will not call again because the current alarm condition has been acknowledged, unless the alarm still exists and the reminder call has been enabled.

If the correct PIN number is not entered within 4 seconds the High Temperature Guard will repeat the warning message. This warning message can be repeated up to 2 times by changing the programmed value. See the **Programming Repeat Warning Messages** section.

If the correct PIN number is not entered the High Temperature Guard will

call the next programmed contact telephone number.

If the High Temperature Guard has called all programmed contact numbers without having the correct PIN number entered, it will wait 20 minutes and repeat the sequence until the alarm condition goes away or the High Temperature Guard receives confirmation either locally or remotely.

How can I connect the High Temperature Guard to a Phone Line which has a fax or answering machine connected to it?

Program the High Temperature Guard to answer after one more ring than the other device. This allows the other device to always answer first. To call and access the High Temperature Guard

1. Dial the phone number
2. Hang up one ring before the other device answers.
3. Wait no longer than 30 seconds, then dial the phone number again.
4. The High Temperature Guard will answer.

For Example:

A fax machine on the same line as the High Temperature Guard is set to answer after 4 rings. The High Temperature Guard is programmed to answer after 5 rings. To access the High Temperature Guard, dial the number, let it ring three times, then hang up. Wait 20 seconds and call again. After two rings, the High Temperature Guard will answer.

Where is the 20 / 30 Hour Extended Batteries?

If your unit has been ordered with an extended battery, it is installed at the factory and is inside the VM520.

How long does it take to charge the battery?

The rechargeable batteries used in the High Temperature Guard are trickle charged and can take up to a week to reach full capacity. The batteries are charging whenever the monitor is powered on.

Troubleshooting

For more technical support please refer to:

www.TemperatureGuard.com/support

Verifying telephone communication

To verify telephone communications, perform the following test.

- 1 Using another phone line, call the High Temperature Guard and verify that it answers the phone.
- 2 Verify at least one programmed telephone number.
- 3 Hang up.
- 4 Call the High Temperature Guard again.
- 5 Enter #999 for the PIN.
- 6 Hang up.
- 7 The High Temperature Guard will perform a test call to your programmed telephone number's.

- ▶ Do not enter your PIN if you would like the High Temperature Guard to continue calling any remaining programmed telephone numbers.
- 8 Watch the display and note any messages present.

If the High Temperature Guard does not answer the phone

Verify that the phone line is a standard analog telephone line. Digital phone lines are not compatible with the High Temperature Guard.

Verify that the phone line is working. Connect a standard phone to the line intended for the High Temperature Guard. Verify that there is a dial tone. Check that the phone line is plugged in securely.

Verify that the High Temperature Guard is powered up and some data is being displayed on the display.

If the High Temperature Guard does not call out

Perform the telephone communication verification procedure. Connect a phone to the line intended for the High Temperature Guard. Verify that there is a dial tone.

Check that the phone line is plugged in securely

Verify that the High Temperature Guard is powered up and the status light is blinking

Verify that the High Temperature Guard is programmed correctly. Call up the High Temperature Guard and verify the programmed phone numbers and limits.

Verifying Network Connectivity (DCP-E units)

When first plugging in the unit or connecting the LAN cable, the LEDs on the Ethernet jack will begin to blink first orange and then green. When fully powered up the left LED will be on steady green and the right LED will blink green.

Link LED (Left Side)		Activity LED (Right Side)	
Color	Meaning	Color	Meaning
Off	No Link	Off	No Activity
Amber	10 Mbps	Amber	Half-Duplex
Green	100 Mbps	Green	Full-Duplex

Accessing advanced network setup

To set either the Subnet Mask or Gateway Address of the device, access the advanced network setup by entering:

http://{Device IP Address}/ltx_conf.html

Click on the “Server Properties” button.

Enter the Subnet Mask and/or Gateway Address and click “Update Settings”

If the status web page does not display/load correctly (DCP-E units)

Verify that you have the latest version of Java loaded on your computer. Go to www.java.com to download the latest version.

FCC PART 68 INFORMATION

This equipment complies with Part 68 of the FCC Rules. The FCC Part 68 Label is located on the bottom of the unit. This label contains the FCC Registration Number and Ringer Equivalence Number (REN) for this equipment. If requested, this information must be provided to your telephone company.

The REN is useful to determine the quantity of devices you may connect to your telephone line and still have all of those devices ring when your telephone number is called. In most, but not all areas, the sum of the RENs of all devices connected to one line should not exceed five (5.0). To be certain of the number of devices you may connect to your line, as determined by the REN, you should contact your local telephone company to determine the maximum REN for your calling area.

Connection to the telephone network should be made by using standard modular telephone jacks, type RJ11. The plug and/or jacks used must comply with FCC Part 68 rules. If this telephone equipment causes harm to the telephone network, the telephone company will notify you in advance that temporary discontinuance of service may be required. But if advance notice isn't practical, the telephone company will notify the customer as soon as possible. Also, you will be advised of your right to file a complaint with the FCC if you believe it is necessary.

The telephone company may make changes in its facilities, equipment, operations or procedures that could affect the proper functioning of your equipment. If they do, you will be notified in advance in order for you to make necessary modifications to maintain uninterrupted service.

This equipment may not be used on coin service provided by the telephone company. Connection to party lines is subject to tariffs.

If trouble is experienced with this unit, for repair or warranty information, please contact customer service at the address and phone listed below. If the equipment is causing harm to the network, the telephone company may request that you disconnect the equipment until the problem is resolved.

DO NOT DISASSEMBLE THIS EQUIPMENT. It does not contain any user serviceable components.

Limited Warranty:

1. Warrantor: Dealer, Distributor, Retailer, and Manufacturer
2. Warranty and Remedy

We believe that this is a high quality product. Although we test all products for proper functionality, we cannot guaranty that there will never be a defective unit, or that a unit will function on every phone line and all communication equipment in existence. For this reason, it must be clear that the **Warrantors are not insuring your premises or guaranteeing that there will not be damage to your person or property if you use this Product.** If this warranty is unacceptable please return the unused Product for a full refund.

One Year Limited Warranty - Microtechnologies warrants its products to be free from defects in material and workmanship under normal use for one year, and is not responsible for consequential damage or installation costs of any nature. In event that the Product does not conform to this Warranty at any time during the period of one year from original purchase date, Warrantor will repair the defect and return it to you at no charge. **Important: The Warranty is limited to replacement of the Product ONLY.** Secondly, because every phone line differs, we strongly encourage you to test this Product in its actual application. This should include a full test, involving the Product actually dialing to its designated location and someone verifying the proper response.

This warranty shall terminate and be of no further effect at the time the Product is 1) damaged by extraneous causes such as fire, water, lightning, etc. or not maintained as reasonable and necessary: 2) modified: 3) improperly installed: 4) repaired by someone other than the Warrantor: 5) used in a manner or purpose for which the Product was not intended.

WARRANTORS' OBLIGATION UNDER THIS WARRANTY IS LIMITED TO REPAIR OR REPLACEMENT OF THE PRODUCT ONLY. THIS WARRANTY DOES NOT COVER PAYMENT OR PROVIDE FOR THE REIMBURSEMENT OF PAYMENT FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES.

It must be clear that the Warrantors are not insuring your premises or guaranteeing that there will not be damage to your person or property if you use this Product. The Warrantors shall not be liable under any circumstances for damage to your person or property or some other person or that person's property by reason of the sale or use of this Product, or its failure to operate in the manner in which it is designed. The Warrantor's liability, if any, shall be limited to the original cost of the Product only. Use of this Product is at your own risk.

3. Procedures for obtaining performance for Warranty:

In the event that the Product does not conform to this Warranty, the Product should be shipped or delivered freight prepaid to a Warrantor with evidence of original purchase. If in any way you are not comfortable with the product or its Limited Warranty, we encourage you to return it unused for a full refund.

Microtechnologies, Inc.
44 Washington Avenue, Suite 8
Berlin, CT 06037
860-829-2710 ph
860-356-4823 fax
www.TemperatureGuard.com
sales@TemperatureGuard.com

R5202C